## PosiTest HHDG Verifier

Standalone volt meter (crest meter, jeep meter) for verifying the accuracy and operation of ALL continuous type DC holiday detectors



Features...

Ideal for field/laboratory verification of continuous DC holiday detectors

Wide measurement range: 0.5 - 30 kV

Simple two step operation

- Lightweight/Portable requires no external power source
- Certificates of Calibration showing traceability to NIST included
- Two year warranty
- Made in USA

## **EASY OPERATION**

Step 1. Ensure that the ground lead is plugged into the PosiTest HHD C Verifier and that the other end of the ground lead is connected to the ground lead of the high voltage holiday detector that is being verified.

**Step 2.** Turn the **PosiTest HHD C Verifier** on by pressing and releasing the power button. Once powered on, the verifier continuously monitors the voltage on the probe end of the verifier. The verifier will update the display when the probe is touching an exposed electrode of a holiday detector. The voltage displayed on the verifier should match the voltage displayed by the detector within the combined tolerance of both units.

<b>DEVICE COMES COMPLETE</b> with verifier, 1.8 m (6') ground
wire, 3 AAA batteries, instructions, Long Form Certificate
of Calibration traceable to NIST, two year warranty.

**SIZE:** 43 x 5 x 5 cm (17" x 2" x 2")

WEIGHT: 476 g (1.05 lbs.)

Specifications		
Voltage Range	0.5 – 30 kV	
Resolution	0.5 kV – 1 kV: 10 Volt Steps 1 kV – 30 kV: 100 Volt Steps	
Accuracy	<u>+</u> 5%	
Operating Temperature	-20° to 60°C (-4° to 140°F)	

Conforms to ASTM D4787/D5162/G62, ISO 29601, NACE SP0188/ SP0274/SP0490, AS3894.1



